

1200W 120V Line Conditioner - Automatic Voltage Regulator (AVR), AC Surge Protection, 4 Outlets

MODEL NUMBER: LC1200



Maintains usable 120V nominal output to sensitive electronics during severe brownouts and overvoltages. Prevents surges and spikes from damaging circuitry. Filters out potentially disruptive line noise.

Description

The LC1200 1200W 120V Line Conditioner - Automatic Voltage Regulator adjusts under- and overvoltages to provide safe, computer-grade AC power that meets ANSI C84.1 specifications. The automatic voltage regulation (AVR) offers three levels of voltage stabilization that corrects undervoltages as low as 89V and overvoltages as high as 147V back to regulated 120V nominal power. Providing optimum voltage conditions not only extends the life of your equipment, but also keeps your equipment working through brownouts and prolonged overvoltage conditions.

A network-grade 1200-joule surge suppression rating exceeds the IEEE-587 standard for surge suppression (both categories A and B) and prevents even the strongest spikes from inflicting damage, data loss or corruption and audio/video performance problems on your connected equipment. EMI/RFI noise filtering protects your AC line from disruptive electromagnetic and radio interference.

Just connect the space-saving NEMA 5-15P right-angle plug with 7-ft. (2.13 m) cord to an AC power source, and plug up to four devices into the NEMA 5-15R outlets. You can monitor AC power, incoming voltage level and AC line status using the seven diagnostic LEDs on the front panel. The compact LC1200 fits comfortably into your computer or home theater setup.

Features

Protects Valuable Electronics Rated at 120V/1200W/10A Ideal for computers, routers, modems, printers, home theater components and point-of-sale equipment Connect up to 4 electronic devices to the rear NEMA 5-15R outlets 7-ft. (2.13 m) cord with NEMA 5-15P right-angle plug for easier connection in tight spaces Compact unit (7.25 in. high) fits comfortably into your computer or home theater setup

Automatic Voltage Regulation (AVR) Monitors incoming AC power and keeps equipment working through brownouts and prolonged overvoltage conditions Corrects undervoltages as low as 89V and overvoltages up to 147V

AC Line Surge Suppression 1200 joules of surge suppression protects against potentially harmful power surges and spikes Includes full normal (H-N) and common (N-G/H-G) line surge suppression

EMI/RFI Line Noise Filtering Removes electromagnetic and radio frequency interference that can disrupt or damage your equipment's performance

Built-In Diagnostics Front-panel LEDs indicate AC power, incoming voltage level and line status Rear on/off switch provides one-touch power control over all components

Highlights

- Ideal for computers, routers, modems and home theater components
- Corrects under- and overvoltages in 89V–147V range
- Protects against spikes with 1200 joules of surge suppression
- Monitors power status with front-panel diagnostic LEDs
- Features 4 NEMA 5-15R rear outlets

Package Includes

- LC1200 1200W 120V Power Conditioner
- Owner's Manual



Specifications

| OVERVIEW | |
|-------------------------------------|--|
| UPC Code | 037332040022 |
| INPUT | |
| Plug Type | Right-angle NEMA 5-15P input plug |
| Input Cord Length (ft.) | 7 |
| Input Cord Length (m) | 2.13 |
| OUTPUT | |
| Output (VA) | 1200 |
| Output (Watts) | 1200 |
| Nominal Output Voltage(s) Supported | 120V |
| Output Receptacles | (4) 5-15R |
| VOLTAGE REGULATION | |
| Voltage Regulation Description | Maintains usable 120V nominal voltage during brownouts as low as 89VAC and over-voltages as high as 147VAC. Input voltages between 114V~127V are passed through unchanged. |
| Overvoltage Correction | Input voltages over 128V (+/-3V) are reduced by 10% |
| Brownout Correction | Input voltages between 113V (+/-3V) and 103V (+/-3V) are boosted by 9%. |
| Severe Brownout Correction | Input voltages below 102V (+/-3V) are boosted by 19%. |
| USER INTERFACE, ALERTS & CONTROLS | |
| Front Panel LEDs | 7 LEDs show incoming voltage status, protection present and line fault conditions |
| SURGE / NOISE SUPPRESSION | |
| UPS AC Suppression Joule Rating | 1200 |
| EMI / RFI AC Noise Suppression | 75 dB |
| PHYSICAL | |
| Form Factors Supported | Small Tower |
| Material of Construction | Plastic |
| Shipping Dimensions (hwd / cm) | 19.56 x 25.65 x 22.10 |
| Shipping Dimensions (hwd / in.) | 7.70 x 10.10 x 8.70 |
| Shipping Weight (kg) | 4.04 |
| Shipping Weight (lbs.) | 8.90 |
| Unit Dimensions (hwd / cm) | 18.4 x 15.2 x 17.8 |



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

| | |
|--|--|
| Unit Dimensions (hwd / in.) | 7.25 x 6 x 7 |
| STANDARDS & COMPLIANCE | |
| Certifications | Tested to UL1012 (USA), cUL1012 (Canada), NOM (Mexico) |
| WARRANTY | |
| Product Warranty Period (Worldwide) | 2-year limited warranty |
| Connected Equipment Insurance (U.S., Canada & Puerto Rico) | \$25,000 Ultimate Lifetime Insurance |

© 2021 Tripp Lite. All rights reserved. All product and company names are trademarks or registered trademarks of their respective holders. Use of them does not imply any affiliation with or endorsement by them. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Tripp Lite uses primary and third-party agencies to test its products for compliance with standards. See a list of Tripp Lite's testing agencies: <https://www.tripplite.com/products/product-certification-agencies>