



GUC232A

USB to Serial RS-232 Adapter

Connect legacy RS-232 serial devices to your USB-equipped computer with this adapter. Supporting up to 230Kbps, it's perfect for modems, printers, and more. Features plug-and-play installation and a 16" cable for flexible use.



Features

- Add one serial port to your PC or Mac via USB connector
- Converts older serial devices to USB connection
- USB 1.1 and USB 2.0 compatible
- 16" cable length
- Supports the RS-232 Serial interface
- Supports automatic handshake mode
- Up to 230Kbps data transfer rate
- Supports remote wakeup and power management
- Provides a 96 byte buffer for each upstream and downstream data transfer
- Easy Installation
- No IRQ required

Requirements

For PC Users

- Windows® 10, Windows® 11
- Available USB port

For Mac Users

- Mac OS X 10.3.9 through 10.14
- Available USB port

Package Contents

- GUC232A USB to Serial adapter cable
- User Manual
- Warranty/Registration Card



Specifications

FUNCTION	GUC232A	DIMENSIONS	GUC232A
Housing		POP Information	
Case	Plastic	10" Peg Hook	5
Power Consumption	90mA	6" Peg Hook	3
LEDs		Unit Dimensions	
On Line	1	Height	.6" (1.6cm)
Operating Temperature	41 to 104 degree Fahrenheit	Length	16.6" (42.2cm)
Storage Temperature	-4 to 140 degree Fahrenheit	Width	1.3" (3.3cm)
USB Specification	USB 1.1 compliant	Unit Package Dimensions	
Transfer Rate	Up to 230Kbps	Height	6.2" (15.7m)
Humidity	20-80% RH, (Non Condensing)	Width	4.9" (12.5cm)
Cable Length	14 in. (40.64 cm.)	Depth	1.6" (4.1cm)
Power Connections	Bus powered	Master Carton	
International - Languages	English	Height	8.1" (20.6cm)
		Width	10.9" (27.6cm)
		Depth	15.5" (39.4cm)
		Master Carton Qty.	24
		Weight	
		Master Carton Wt.	7.9lbs (3.6kg)
		Unit Pack Wt.	.30 lbs (.14kg)
		Unit Wt.	.10lbs (.05kg)